



Lighting Control Gear & Accessories

Emergency Module Selection Chart

Modules (1 of 3)

ELG Ref	9420111A	9420112B	9420012A	9420114A	9420113A	9420010A	9420011A	9420012A	9420013A	9420014A
No. of Cells	3-CELL	4-CELL	4-CELL	5-CELL	5-CELL	3-CELL	3-CELL	4-CELL	5-CELL	5-CELL
Manufacturer	Tridonic	Tridonic	Tridonic	Tridonic	Tridonic	Ventilux	Ventilux	Ventilux	Ventilux	Ventilux
Mnf. Ref	EM33B	EM34A	EM34B	EM35A	EM35B	HFM 3-18	HFM 3-36	HFM 4-58	HFM 5-70	HFM 5-54
2D										
10W		30		39						
16W		24		31						
21W		20		25						
28W		19		21						
38W				15						
T5										
4W		30		37		39				
6W		32		40		33				
8W		32		40		31				
13W		30		37						23
14W		21		32						23
21W		21*(2)		21*(2)						17
24W				19						14
28W					14**					12
39W										16
54W										4
T8										
18W	10		12	18	13	16				
30W	9		13	18	14					
36W	8		10	16	10		9	9		
58W			7		7			8		
70W					7				7	
T12										
40							8	9		
65								7		
85									9	

Numbers Denote % light output factors

*(2) 2 Hours Only

** Only to be used in maintained mode

Tel: 0870 445 0755 or Fax: 0870 445 0756

Or call our Lamp and Gear sales hotline on 0870 445 0000

ELG Ref	9420111A	9420112B	9420012A	9420114A	9420113A	9420010A	9420011A	9420012A	9420013A	9420014A
No. of Cells	3-CELL	4-CELL	4-CELL	5-CELL	5-CELL	3-CELL	3-CELL	4-CELL	5-CELL	5-CELL
Manufacturer	Tridonic	Tridonic	Tridonic	Tridonic	Tridonic	Ventilux	Ventilux	Ventilux	Ventilux	Ventilux
Manf. Ref	EM33B	EM34A	EM34B	EM35A	EM35B	HFM 3-18	HFM 3-36	HFM 4-58	HFM 5-70	HFM 5-54
TC-L / PLL										
18W		18		19				14		
24W		17		20						
34W			9**	19						
36W			9**	20			7	12		
40W			8**		10**					
55W			5**		6**					5
TC-SEL / PL-S										
7W						29				
9W						21				
11W								17		
TC-DEL / PL-C										
10W						38				
13W								26		
18W						15		19		
26W								19		
TC-TEL / PL-T										
18W								17		25
26W										19
32W										14
42W										11

Numbers Denote % light output factors

*(2) 2 Hours Only

** Only to be used in maintained mode

Tel: 0870 445 0755 or Fax: 0870 445 0756

Or call our Lamp and Gear sales hotline on 0870 445 0000

Emergency Module Selection Chart

Ballast and Module

(3 of 3)

ELG Ref	9420210S	9420211S	9420210E	9420328E	9420329E
No. of Cells	3-CELL	4-CELL	4-CELL	4-CELL	4-CELL
Manufacturer	Harvard	Harvard	Tridonic	Tridonic	Tridonic
Mnf. Ref	DE28	DE38	PC1X28-34DDCOMBO	PC1X58/34COMBO	PC2X58/34COMBO
2D					
28W	12		12		
38W		12			
T8					
58W				7	7 (1 lamp only)

Numbers Denote % light output factors

*(2) 2 Hours Only

** Only to be used in maintained mode

Emergency Module Selection Chart

L. V. Combi Unit

ELG Ref	94200013B
No. of Cells	Integral
Manufacturer	Ventilux
Mnf. Ref	THSP20/NM3
Dichroic	
12V, 20W	20W

Tel: 0870 445 0755 or Fax: 0870 445 0756

Or call our Lamp and Gear sales hotline on 0870 445 0000

ELG Ref	942--0310A	942--0311A	942--0312A
Type	4 POLE HF	4 POLE HF	4 POLE HF
No. of Cells	3	4	5
Mackwell No	SM478	SM480	SM484
2D			
10W	26	30	
16W	18*	27*	
21W		24*	29*
28W		16*	21*
38W*			18*
T5			
4W	30	31	59
6W	31	35	62
8W	30	32	62
13W	19	34	30
14W	20	24*	25*
21W		19*	25*
15W		15*	32
18W		15*	32
30W		11*	15*
36W		11*	15*
20W			28
40W			12

numbers denote ballast lumen factor (BLF)

* See Relevant Data Sheet

Tel: 0870 445 0755 or Fax: 0870 445 0756

Or call our Lamp and Gear sales hotline on 0870 445 0000